



5200 Beethoven Street, Los Angeles, CA 90066  
 TEL: (310)306-5556 • FAX: (310)821-7413  
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

**MODEL 5402**  
**500-1500 MHz**  
**200 WATTS**  
**LINEAR POWER RF AMPLIFIER**

**Solid State  
 Broadband High Power  
 RF Amplifier**

The 5402 is a 200 Watt broadband amplifier that covers the 500-1500 MHz frequency range. This amplifier utilizes Class A linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 5402 comes with an extended multiyear warranty backed by Ophir RF's commitment to total customer satisfaction.

	<u>Parameter</u>	<u>Specification @ 25° C</u>
<b><u>Electrical</u></b>		
1	Frequency Range	500-1500 MHz
2	Saturated Output Power	200 Watts Rated
3	Power at P1dB	100 Watts Minimum
4	Small Signal Gain	+53 dB Minimum
5	Gain Flatness	± 3.5 dB Maximum
6	IP <sub>3</sub>	+59 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc min @ 100 Watts
9	Spurious Signals	< -60 dBc typical @ 100 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	2500 Watts Maximum
12	AC Input	180 – 240 VAC, single phase
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	Class A
<b><u>Mechanical</u></b>		
16	Dimensions	19" x 8.75" x 26"
17	Weight	110 Lbs.
18	RF Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<b><u>Environmental</u></b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice

**ORDERING MODELS**

- ◇ RE - Rear RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ FE - Front RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ R - Rear RF Connector model
- ◇ F - Front RF Connector model



**FE MODEL SHOWN**



5200 Beethoven Street, Los Angeles, CA 90066  
TEL: (310)306-5556 • FAX: (310)821-7413  
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

<b>MODEL 5402</b> <b>500-1500 MHz</b> <b>200 WATTS</b> <b>LINEAR POWER RF AMPLIFIER</b>
--

### FRONT PANEL CONTROLLER FEATURES (Optional)

- ◇ - Forward Power Monitoring
- ◇ - Reflected Power Monitoring
- ◇ - Gain Control (20 dB dynamic range of adjustment)
- ◇ - Fault Status
- ◇ - Full Protection Of any VSWR Condition, Open or Short, into any Phase Angle
- ◇ - Remote Control Access via the Ethernet, RS-232, or IEEE-488 Communications ports
- ◇ - Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, or input RF level
- ◇ - Standby/Enable Control
- ◇ - Front Panel Display for easy viewing of System Status Locally
- ◇ - Keypad buttons for full local control

### CIRCUIT CONTROL (WITH FRONT PANEL CONTROLLER)

- ◇ - Standby (amplifier disable)
- ◇ - Gain/power setting with 20dB range
- ◇ - VSWR protection Reset
- ◇ - ALC On/ Off

### CIRCUIT INDICATIONS (WITH FRONT PANEL CONTROLLER)

- ◇ - Forward Power
- ◇ - Reflected power
- ◇ - VSWR Fault
- ◇ - Temp Fault
- ◇ - Gain Setting (VVA) percentage

### CIRCUIT PROTECTIONS

- ◇ - Thermal Overload
- ◇ - Over Current
- ◇ - Over Voltage
- ◇ - Open or Short VSWR Conditions (With Front Panel Controller)

### RFPA SYSTEM OPTIONS

- ◇ - Switched Filter Bank
- ◇ - Input Power Requirements
- ◇ - Ruggedized Version
- ◇ - Cabinet Requirements
- ◇ - Outdoor Version
- ◇ - Sample Ports
- ◇ - Racking Options
- ◇ - Many More!
- ◇ - **Consult Factory with Specific Requirements**

