



5200 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5243
700-3000 MHz
70 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High Power
 RF Amplifier**

The 5243 is a 70 Watt broadband amplifier that covers the 700-3000 MHz frequency range. This amplifier utilizes Class A linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5243 comes with an extended multiyear warranty backed by Ophir RF's commitment to total customer satisfaction.

	<u>Parameter</u>	<u>Specification @ 25° C</u>
<u>Electrical</u>		
1	Frequency Range	700-3000 MHz
2	Saturated Output Power	70 Watts Typical
3	Power at P1dB	45 Watts Minimum
4	Small Signal Gain	+49 dB Minimum
5	Gain Flatness	± 1.5 dB Maximum
6	IP ₃	+52 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 45 Watts
9	Spurious Signals	< -60 dBc typical @ 45 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	900 Watts Maximum
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+6 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	Class A
<u>Mechanical</u>		
16	Dimensions	19" x 5.25" x 21"
17	Weight	55 Lbs.
18	RF Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice



FE MODEL SHOWN

ORDERING MODELS

- RE - Rear RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- FE - Front RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- R - Rear RF Connector model
- F - Front RF Connector model



5200 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

<p>MODEL 5243</p> <p>700-3000 MHz 70 WATTS LINEAR POWER RF AMPLIFIER</p>
--

FRONT PANEL CONTROLLER FEATURES (Optional)

- Forward Power Monitoring
- Reflected Power Monitoring
- Gain Control (20 dB dynamic range of adjustment)
- Fault Status
- Full Protection Of any VSWR Condition, Open or Short.
- Remote Control Access via the Ethernet, RS-232, or IEEE-488
- Communications ports
- Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, or input RF level
- Standby/Enable Control
- Front Panel Display for easy viewing of System Status Locally
- Keypad buttons for full local control

CIRCUIT CONTROL (WITH FRONT PANEL CONTROLLER)

- Standby (amplifier disable)
- Gain/power setting with 20dB range
- VSWR protection Reset
- ALC On/ Off

CIRCUIT INDICATIONS (WITH FRONT PANEL CONTROLLER)

- Forward Power
- Reflected power
- VSWR Fault
- Temp Fault
- Gain Setting (VVA) percentage

CIRCUIT PROTECTIONS

- Thermal Overload
- Over Current
- Over Voltage
- Open or Short VSWR Conditions (With Front Panel Controller)

RFPA SYSTEM OPTIONS

- Switched Filter Bank
- Input Power Requirements
- Ruggedized Version
- Cabinet Requirements
- Outdoor Version
- Sample Ports
- Racking Options
- Many More!

Consult Factory with Specific Requirements

