5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5254

0.7 - 2.5 GHz
150 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5254 is a 150 Watt broadband amplifier that covers the 0.7 – 2.5 GHz frequency range. This small and lightweight amplifier utilizes Class A linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR$_{RF}$ amplifiers, the 5254 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	0.7 – 2.5 GHz
2	Saturated Output Power	150 Watts rated
3	Power Output @ 1dB Comp.	80 W minimum
4	Small Signal Gain	+52 dB min
5	Small Signal Gain Flatness	± 3.0 dB max
6	IP_3	+56 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 80 W -15 dBc maximum @ 80 W
9	Spurious Signals	< -60 dBc maximum @ 100 W
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	1,500 Watts maximum
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A
Mechanical		
16	Dimensions	19" x 5.25" x 26"
17	Weight	72 lbs.
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0º C to +50º C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice

CIRCUIT PROTECTIONS

◊ Thermal Overload
◊ Over Current
◊ Over Voltage

CIRCUIT CONTROL

◊ Standby (amplifier disable)
◊ Gain/power setting with 20 dB range
◊ VSWR protection Reset
◊ ALC On/ Off

CIRCUIT INDICATIONS

◊ Forward Power
◊ Reflected power
◊ VSWR Fault
◊ Temp Fault
◊ Gain Setting (VVA) percentage

FE Model Shown

ORDERING MODELS

◊ RE - R model with Ethernet, IEEE488 and RS232
◊ FE - F model with Ethernet, IEEE488 and RS232

03/15 Approved By: _____ Date: _____