



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5303075
0.8 – 4.2 GHz
1.5 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High
 Power RF Amplifier**

The 5303075 is a 1.5 Watt broadband amplifier that covers the 0.8 – 4.2 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5303075 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	0.8 – 4.2 GHz
2	Saturated Output Power	1.5 Watts typical
3	Power Output @ 1dB Comp.	1.2 Watts min
4	Small Signal Gain	+31 dB min
5	Gain Flatness	± 2.0 dB max
6	IP ₃	+41 dBm typical
7	Input VSWR	2.2:1 max
8	Harmonics	-20 dBc typical @ 1.2 Watt
9	Spurious Signals	< -60 dBc typical @ 1.2 Watt
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	800 mA max
12	DC Input	13 VDC nominal
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	3.0" x 2.2" x 0.6"
17	Weight	0.5 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
Environmental		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



Approved By: _____ Date: _____