



5300 Beethoven Street, Los Angeles, CA 90066  
 TEL: (310)306-5556 • FAX: (310)577-9887  
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

**MODEL 4134**

**2.0-30.0 MHz**  
**12000 WATTS**  
**LINEAR POWER RF AMPLIFIER**

## Solid State Broadband High Power RF Amplifier

The 4134 is a 12000 Watt broadband amplifier that covers the 2.0-30.0 MHz frequency range. This amplifier utilizes Class A linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

This amplifier is the perfect choice for transmitting financial data long distance to a remote secure location.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 4134 comes backed by Ophir RF's commitment to total customer satisfaction.

	<u>Parameter</u>	<u>Specification @ 25° C</u>
<b><u>Electrical</u></b>		
1	Frequency Range	2.0-30.0 MHz
2	Saturated Output Power	12000 Watts
3	Power Output @ 1dB Comp.	10000 Watts
4	Small Signal Gain	+72 dB Minimum
5	Gain Flatness	+/- 3.0 dB Max. +/- 1.0 dB over 100KHz BW
6	Input VSWR	2:1 max
7	Harmonics	-15 dBc maximum @ 10 KW
7	Spurious Signals	-60 dBc typical @ 10 KW
9	Input/Output Impedance	50 Ohms Nominal
10	AC Input Power	30,000 Watts Maximum
11	AC Input	187-264 VAC, 3Ø "Delta" (4-wire)
12	Nominal RF Input	0 dBm
13	<b>RF Input Overdrive</b>	<b>+10 dBm Maximum</b>
14	RF Input Signal Format	CW/AM/FM/PM
15	Class of Operation	A/AB
<b><u>Mechanical</u></b>		
16	Dimensions* (W x H x D)	Two Cabinets: 19" x 60" x 36"
17	Weight*	600 lb. Maximum each cabinet
18	RF Connectors	RF Input: Type-N RF Output: 1&5/8 DIN
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<b><u>Environmental</u></b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice



5300 Beethoven Street, Los Angeles, CA 90066  
TEL: (310)306-5556 • FAX: (310)577-9887  
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

**MODEL 4134**  
**2.0-30.0 MHz**  
**12000 WATTS**  
**LINEAR POWER RF AMPLIFIER**

## FRONT PANEL CONTROLLER FEATURES

- ◇ - Forward Power Monitoring (dBm or Watts)
- ◇ - Reflected Power Monitoring (dBm or Watts)
- ◇ - Gain Control (20 dB dynamic range of adjustment)
- ◇ - Fault Status
- ◇ - Full Protection Of any VSWR Condition, Open or Short.
- ◇ - Remote Control Access via the Ethernet, RS-232, or IEEE-488 Communications ports
- ◇ - Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, or input RF level
- ◇ - Standby/Enable Control
- ◇ - Front Panel Display for easy viewing of System Status Locally
- ◇ - Keypad buttons for full local control

## CIRCUIT PROTECTIONS

- ◇ - Thermal Overload
- ◇ - Over Current
- ◇ - Over Voltage
- ◇ - Open or Short VSWR

## CIRCUIT CONTROL

- ◇ - Standby (amplifier disable)
- ◇ - Gain/power setting with 20dB range
- ◇ - VSWR protection Reset
- ◇ - ALC On/ Off

## CIRCUIT INDICATIONS

- ◇ - Forward Power
- ◇ - Reflected power
- ◇ - VSWR Fault
- ◇ - Temp Fault
- ◇ - Gain Setting (VVA) percentage



Proudly made  
in the U.S.A.





5300 Beethoven Street, Los Angeles, CA 90066

TEL: (310)306-5556 • FAX: (310)577-9887

WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 4134

2.0-30.0 MHz

12000 WATTS

LINEAR POWER RF AMPLIFIER



### ORDERING MODELS

- ◇ RE - Rear RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ FE - Front RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232