



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5803129
0.7 - 4.0 GHz
8 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High
 Power RF Amplifier**

The 5803129 is a 8 Watt broadband amplifier that covers the 0.7 – 4.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5803129 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	0.7 – 4.0 GHz
2	Saturated Output Power	8 Watts typical
3	Power Output @ 1dB Comp.	7 Watts min
4	Small Signal Gain	+38 dB min
5	Gain Flatness	± 2.0 dB max
6	IP ₃	+49 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 8 Watts
9	Spurious Signals	< -60 dBc typical @ 8 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	7 Amps max
12	DC Input	13 Vdc nominal
13	RF Input	+10 dBm Maximum
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	10.55" x 7.0" x 3.9"
17	Weight	12 Lbs.
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink and Airflow Included
Environmental		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



Representation of actual module assembly.

580 Features:
 Heatsink and Fans Included

