



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5903032
0.5 - 500 MHz
8 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High Power
 RF Amplifier**

The 5903032 is an 8 Watt broadband amplifier that covers the 0.5 – 500 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5903032 comes with an extended multiyear warranty backed by Ophir RF's commitment to total customer satisfaction.

INCLUDED FEATURES

- Mounted on a Heat Sink

	<u>Parameter</u>	<u>Specification @ 25° C</u>
<u>Electrical</u>		
1	Frequency Range	0.5 – 500 MHz
2	Saturated Output Power	8 Watts typical
3	Power Output @ 1dB Comp.	4 Watts min
4	Small Signal Gain	+40 dB min
5	Gain Flatness	± 1.0 dB max
6	IP ₃	+42 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 4 Watts
9	Spurious Signals	< -60 dBc typical @ 4 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	3 Amps max
12	DC Input	28 VDC nominal
13	RF Input	-1 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<u>Mechanical</u>		
16	Dimensions	6.5" x 4.5" x 2.5"
17	Weight	3 Lbs.
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Cooling Required
<u>Environmental</u>		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



**SIMILAR MODULE MOUNTED
 ON A HEATSINK**

