



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5303169A
1-1000 MHz
10 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5303169A is a 10 Watt broadband amplifier that covers the 1-1000 MHz frequency range. This small and lightweight amplifier utilizes latest generation Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5303169A comes backed by Ophir RF's commitment to total customer satisfaction.

	Parameter	Specification @ 25° C			Unit of Measure
		Minimum	Nominal	Maximum	
Electrical					
1	Frequency Range	1		1000	MHz
2	Output Power P _{SAT}	10	15		Watts
3	Output Power P _{1dB}	6			Watts
4	Small Signal Gain	43			dB
5	Small Signal Flatness			± 2.0	dB
6	Gain Flatness (P _{sat})			± 1.0	dB
7	IP ₃		46		dBm
8	Input VSWR	2:1			Ratio
9	Harmonics @ 6 Watts		-20		dBc
10	Spurious @ 6 Watts		-60		dBc
11	Input/Output Impedance		50		Ohms
12	DC Input Current @ 10W		3	4	Amps
13	DC Input		28	40	Vdc
14	RF Input for Rated Power			0	dBm
15	Blanking (Rise/Fall)		10		µSec
16	RF Input Signal Format	CW/AM/FM/PM/Pulse			
17	Class of Operation	A/AB			
Mechanical					
18	Dimensions (L x W x H)	6" x 3" x 1"			
19	Weight		2.0		Lbs.
20	RF Input Connector	SMA female			
21	RF output Connector	SMA Female			
22	Grounding	Chassis			
23	Cooling	Adequate Heatsink and Air flow Required			
Environmental					
24	Operating Temperature Baseplate	0		50	°C
25	Operating Humidity, Non Condensing			95	%
26	Operating Altitude			10,000	Feet above sea Level
27	MIL-STD 810G Shock and Vibration	Shock Method 514.5 Vibration Method 516.5			

Specifications subject to change without notice.



01/25 Approved By: _____ Date: _____