



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5259
1.0-2.5 GHz
2000 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5259 is a 2000 Watt broadband amplifier that covers the 1.0-2.5 GHz frequency range. This small and lightweight amplifier utilizes Class A linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability, Like all OPHIR_{RF} amplifiers, the 5259 comes with an extended multiyear warranty backed by Ophir RF's commitment to total customer satisfaction.

	<u>Parameter</u>	<u>Specification @ 25° C</u>			
		<u>Minimum</u>	<u>Nominal</u>	<u>Maximum</u>	<u>Unit</u>
<u>Electrical</u>					
1	Frequency Range	1.0		2.5	GHz
2	Power at P _{SAT}	1600	2000		Watts
3	Power at P _{1dB}	1300	1600		Watts
4	Small Signal Gain	63			dB
5	Gain Flatness			±3.5	dB
6	IP ₃		67		dBm
7	Input VSWR			2:1	Ratio
8	Harmonics @ 1000W		-20		dBc
9	Spurious Signal @ 1000W		-60		dBc
10	Input/Output Impedance		50		Ohms
11	AC Input Power			12000	Watts
12	AC Input	208 VAC (± 10%) 3-Phase			
13	RF Input (No Damage)			+3	dBm
14	RF Input Signal Format	CW/AM/FM/PM/Pulse			
15	Class of Operation	Class A			
<u>Mechanical</u>					
16	Dimensions H x W x D	48" x 24" x 32"(H x W x D) 162 x 61 x 81 (H x W x D) cm			
17	Weight	290 Lbs.			
18	RF Connectors	Type-N Female Input 1 5/8" Output			
19	Grounding	Chassis			
20	Cooling	Internal Forced Air			
<u>Environmental</u>					
21	Operating Temperature	0		50	° C
22	Operating Humidity	95% Non-condensing			
23	Operating Altitude	Up to 10,000' Above Sea Level			
24	Shock and Vibration	Normal Truck Transport			

Specifications subject to change without notice





5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5259
1.0-2.5 GHz
2000 WATTS
LINEAR POWER RF AMPLIFIER

FRONT PANEL CONTROLLER

- ◇ - Forward Power Monitoring (dBm or Watts)
- ◇ - Reflected Power Monitoring (dBm or Watts)
- ◇ - Gain Control (20 dB dynamic range of adjustment)
- ◇ - Fault Status
- ◇ - Full Protection Of any VSWR Condition, Open or Short, into any Phase Angle
- ◇ - Remote Control Access via the Ethernet, RS-232, or IEEE-488 Communications ports
- ◇ - Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, or input RF level
- ◇ - Standby/Enable Control
- ◇ - Front Panel Display for easy viewing of System Status Locally
- ◇ - Keypad buttons for full local control

CIRCUIT PROTECTIONS

- ◇ - Thermal Overload
- ◇ - Over Current
- ◇ - Over Voltage
- ◇ - Open or Short VSWR Conditions

CIRCUIT CONTROL

- ◇ - Standby (amplifier disable)
- ◇ - Gain/power setting with 20dB range
- ◇ - VSWR protection Reset
- ◇ - ALC On/ Off

CIRCUIT INDICATION

- ◇ - Forward Power
- ◇ - Reflected power
- ◇ - VSWR Fault
- ◇ - Temp Fault
- ◇ - Gain Setting (VVA) percentage

RFPA SYSTEM OPTIONS

- ◇ - Switched Filter Bank
- ◇ - Input Power Requirements
- ◇ - Ruggedized Version
- ◇ - Cabinet Requirements
- ◇ - Outdoor Version
- ◇ - Sample Ports
- ◇ - Racking Options
- ◇ - Front Panel Controller ("E" Option)
- ◇ - **Consult Factory with Specific Requirements**

Specifications subject to change without notice



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5259
1.0-2.5 GHz
2000 WATTS
LINEAR POWER RF AMPLIFIER



Specifications subject to change without notice



ORDERING MODELS

- ◇ RE - Rear RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ FE - Front RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232



02/26 Approved By: _____ Date: _____