



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5304050
6.0-18.0 GHz
10 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High Power
 RF Amplifier**

The 5304050 is a 10 Watt broadband amplifier that covers the 6.0-18.0 GHz frequency range. This small and lightweight amplifier utilizes Class AB linear Gallium Nitride (GaN) devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5304050 comes backed by Ophir RF's commitment to total customer satisfaction.



	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	6.0-18.0 GHz
2	Rated Output Power	10 Watts Nominal
4	Small Signal Gain	+41 dB min
5	Gain Flatness 6.0-16.0 GHz 16.0-18.0 GHz	± 4.0 dB Nominal ± 4.0 dB Nominal
6	IP ₃	+45 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 5 Watts
9	Spurious Signals	< -60 dBc typical @ 5 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	8.0 Amps Maximum
12	DC Input	18 VDC Nominal
13	RF Input	0 dBm max
14	Blanking (Rise/Fall)	10 µSec Maximum
15	RF Input Signal Format	CW/AM/FM/PM/Pulse
16	Class of Operation	AB
Mechanical		
17	Dimensions	6" x 3" x 1.1"
18	Weight	1 lb.
19	Connectors	SMA female
20	Grounding	Chassis
21	Cooling	Adequate Heatsink Required
Environmental		
22	Operating Temperature	-40° C to +85° C
23	Operating Humidity	95% Non-condensing
24	Operating Altitude	Up to 40,000' Above Sea Level
25	Shock and Vibration	MIL-STD 810G (Method 514.6)

SPECIAL FEATURES

- ◇ EXTREMELY BROADBAND
- ◇ HIGHLY EFFICIENT DESIGN
- ◇ WIDE OPERATING TEMPERATURE RANGE
- ◇ SMALL, COMPACT FORM FACTOR

Specifications subject to change without notice.





5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5304050
6.0-18.0 GHz
10 WATTS
LINEAR POWER RF AMPLIFIER

